Speed Queen。

Coin Top Load Washer SWT911

Product Specifications

· · · · · · · · · · · · · · · · · · ·		
Cabinet Dimensions		
Width	25 5/8"	
Depth	28"	
Height	43"	
Work Surface Height	36"	
Basket Volume	2.8 cu. ft.	

Fi	Finish	
Τι	ıb Finish	Stainless Steel

Operation	
Cycle Time	28 - 31 minutes
Cycles/Temperature	Hot, Warm, Cold
Motor HP	1/2 HP, 9.8 Amps
Motor RPM	60 Hz, 1725 or 1140 RPM
Electrical Specs	120/60/1 - 15 Voltage/Hz/Phase/Amps
Spin Speeds	710 RPM
Water Consumption	26.6 Gal/Cycle
Water Factor	9.5 Gal/cu. ft.
Modified Energy Factor	1.26
Hot Water Usage	4 Gal/Cycle
Water Pressure	1.4 - 8.3 psi

Shipping	
Net Weight	190 lb
Shipping Weight	210 lb


Agency Approvals		
Agency Approvals	UL	

For the most accurate information the installation guide should be used for all design and construction purposes. Due to continuous product improvements, design and specifications subject to change without notice. The quality management system of Alliance Laundry Systems' Ripon facility has been registered to ISO 9001:2000.

Features & Benefits

- Heavy-duty components including a stainless steel washtub, all metal transmission and a life for your coin laundry
- Speed Queen's top load washers are compliant to the 2007 U.S. Department of Energy's water and energy efficiency standards for commercial washers. Coin laundry owners benefit from significant savings in water and energy costs.
- Our curved four-vane agitator delivers an industry-best 210° wash stroke that produces unparalleled cleaning results.
- A durable stainless steel washtub keeps your customers clothes looking their best longer. Speed Queen's exclusive stainless steel tub actually becomes smoother with each use, so it won't pill, snag or fray clothes.

commercial-grade cabinet





Available Controls

Available Collinois		
Control	Description	
E-Mech CYCLE EXAMPLE OYCLE EXAMPLE	The E Mech control's straight-forward design offers customers simple water temperature and fabric selections. Cue lights keep customers aware of what wash cycle the washer is in. This control will work with the coin slide manufacturer of the owner's choosing.	